INDUSTRIAL SPARK-IGNITED GENERATOR SET

EPA Certified Stationary Emergency

Standby Power Rating 50 kW, 63 kVA, 60 Hz

Prime Power Rating 45 kW, 56 kVA, 60 Hz





Image used for illustration purposes only

Codes and Standards

Generac products are designed to the following standards:





UL2200, UL6200, UL1236, UL489



CSA C22.2, ULC S601



BS5514 and DIN 6271



SAE J1349



NFPA 37, 70, 99, 110



NEC700, 701, 702, 708



NEMA ICS10, MG1, 250, ICS6, AB1



ANSI C62.41



IBC 2009, CBC 2010, IBC 2012, ASCE 7-05, ASCE 7-10, ICC-ES AC-156 (2012)

Powering Ahead

Generac ensures superior quality by designing and manufacturing most of its generator components, such as alternators, enclosures, control systems and communications software. Generac also makes its own spark-ignited engines, and you'll find them on every Generac gaseous-fueled generator. We engineer and manufacture them from the block up — all at our facilities throughout Wisconsin. Applying natural gas and LP-fueled engines to generators requires advanced engineering expertise to ensure reliability, durability and necessary performance. By designing specifically for these dry, hotter-burning fuels, the engines last longer and require less maintenance. Building our own engines also means we control every step of the supply chain and delivery process, so you benefit from single-source responsibility.

Plus, Generac Industrial Power's distribution network provides all parts and service so you don't have to deal with third-party suppliers. It all leads to a positive owner experience and higher confidence level. Generac spark-ignited engines give you more options in commercial and industrial generator applications as well as extended run time from utility-supplied natural gas.

INDUSTRIAL SPARK-IGNITED GENERATOR SET

EPA Certified Stationary Emergency

STANDARD FEATURES

ENGINE SYSTEM

- · Oil Drain Extension
- Heavy Duty Air Cleaner
- Level 1 Fan and Belt Guards (Open Set Only)
- Stainless Steel Flexible Exhaust Connection
- · Factory Filled Oil and Coolant
- · Critical Silencer
- · Oil Temperature Sender with Alarm
- · Air Filter Restriction Indicator

FUEL SYSTEM

- · NPT Fuel Connection on Frame
- · Primary and Secondary Fuel Shutoff

COOLING SYSTEM

- · Closed Coolant Recovery System
- UV/Ozone Resistant Hoses
- · Factory-Installed Radiator
- 50/50 Ethylene Glycol Antifreeze
- · Radiator Drain Extension

ELECTRICAL SYSTEM

- · Battery Charging Alternator
- Battery Cables
- Battery Tray
- · Rubber-Booted Engine Electrical Connections
- · Solenoid Activated Starter Motor

ALTERNATOR SYSTEM

- UL2200 GENprotect™
- · Class H Insulation Material
- 2/3 Pitch
- · Skewed Stator
- Brushless Excitation
- · Sealed Bearing
- · Full Load Capacity Alternator

GENERATOR SET

- Internal Genset Vibration Isolation
- · Separation of Circuits High/Low Voltage
- · Separation of Circuits Multiple Breakers
- Wrapped Exhaust Piping
- · Standard Factory Testing
- 2 Year Limited Warranty (Standby and Demand Response Rated Units)
- · 1 Year Limited Warranty (Prime Rated Units)

ENCLOSURE (IF SELECTED)

- Rust-Proof Fasteners with Nylon Washers to Protect Finish
- High Performance Sound-Absorbing Material (Sound Attenuated Enclosures)
- Gasketed Doors
- Upward Facing Discharge Hoods (Radiator and Exhaust)
- Stainless Steel Lift Off Door Hinges
- Stainless Steel Lockable Handles
- RhinoCoat™ Textured Polyester Powder Coat Paint

CONTROL SYSTEM



Power Zone® Pro Controller

- NFPA 110 Level 1 Compliant
- · Engine Protective Functions
- · Alternator Protective Functions
- Digital Engine Governor ControlDigital Voltage Regulator
- Multiple Programmable Inputs and Outputs
- Remote Display Capability

Power Zone® Pro Controller Continued

- Remote Communication via Modbus® RTU, Modbus TCP/IP, and Ethernet 10/100, SNMP
- Alarm and Event Logging with Real Time Stamping
- · Expandable Analog and Digital Inputs and Outputs
- · Remote Wireless Software Update Capable
- Built-In Programmable Logic Eliminates the Need for External Controllers Under Most Conditions
- Programmable I/O Channel Properties
- · Built-In Diagnostics

Alarms and Warnings

- · High/Low Oil Pressure
- · High/Low Coolant Level
- High/Low Coolant Temperature
- · Sender/Sensor Failure
- High/Low Oil Temperature
- Over Total kW
- Over/Under Speed
- · Over/Under Voltage
- Over/Under Frequency
- Over Current
- High/Low Battery Voltage

Alarms and Warnings Continued

- Battery Charger Current
- Phase to Phase and Phase to Neutral Short Circuits (I²T Algorithm)

4.3 Inch Color Touch Screen Display

- · Resistive Color Touch Screen
- · Easily Identifiable Icons
- Multi-Lingual
- · On Screen Editable Parameters

Key Function Monitoring

- Three Phase Voltage, Amperage, kW, kVA, and kVAr
- Selectable Line to Line or Line to Neutral Measurements
- Frequency
- Engine Speed
- Engine Coolant Temperature
- Engine Oil Temperature
- · Battery Voltage
- Hourmeter
- · Warning and Alarm Indication
- Diagnostics
 - · Maintenance Events/Information

INDUSTRIAL SPARK-IGNITED GENERATOR SET

EPA Certified Stationary Emergency

CONFIGURABLE OPTIONS

GENERAC* INDUSTRIAL

ENGINE SYSTEM

- o Heater with Shutoff Valves
- o Engine Coolant Heater
- o Oil Heater
- o Level 1 Fan and Belt Guards (Enclosed Units Only)
- o Radiator Duct Adapter (Open Set Only)

FUEL SYSTEM

o NPT Flexible Fuel Line

ELECTRICAL SYSTEM

- o 10A UL Battery Charger
- o Battery Warmer

ALTERNATOR SYSTEM

- o Alternator Upsizing
- o Anti-Condensation Heater
- o Tropical Coating

CIRCUIT BREAKER OPTIONS

- o Main Line Circuit Breaker
- o 2nd Main Line Circuit Breaker
- o 3rd Main Line Circuit Breaker
- Shunt Trip and Auxiliary Contact
- o Electronic Trip Breakers

GENERATOR SET

- o Extended Factory Testing (3-Phase Only)
- o 8 Position Load Center

ENCLOSURE

- o Level 0 Sound Attenuated
- o Level 1 Sound Attenuated
- o Level 2 Sound Attenuated
- Level 2 Sound Attenuated with Motorized Dampers
- o Steel Enclosure
- o Aluminum Enclosure
- Up to 200 MPH Wind Load Rating (Contact Factory for Availability)
- o AC/DC Enclosure Lighting Kit
- o Enclosure Heaters (with Motorized Dampers Only)
- o Door Alarm Switch

CONTROL SYSTEM

- NFPA 110 Compliant 21-Light Remote Annunciator
- o Remote Relay Assembly (8 or 16)
- Remote E-Stop (Break Glass-Type, Surface Mount)
- Remote E-Stop (Red Mushroom-Type, Surface Mount)
- Remote E-Stop (Red Mushroom-Type, Flush Mount)
- o 10A Engine Run Relay
- o Ground Fault Annunciator
- o 120 V GFCI and 240 V Outlets
- o 100 dB Alarm Horn
- Damper Alarm Contacts (with Motorized Dampers Only)

WARRANTY (STANDBY GENSETS ONLY)

- o 2 Year Extended Limited Warranty
- o 5 Year Limited Warranty
- o 5 Year Extended Limited Warranty
- o 7 Year Extended Limited Warranty
- o 10 Year Extended Limited Warranty

ENGINEERED OPTIONS

CONTROL SYSTEM

- o Spare Inputs (x4) / Outputs (x4)
- o Battery Disconnect Switch

GENERATOR SET

- Special Testing
- Battery Box

INDUSTRIAL SPARK-IGNITED GENERATOR SET

EPA Certified Stationary Emergency



APPLICATION AND ENGINEERING DATA

ENGINE SPECIFICATIONS

General

Make	Generac
Cylinder #	4
Туре	In-Line
Displacement - in3 (L)	275.0 (4.5)
Bore: in (mm)	4.5 (114.3)
Stroke: in (mm)	4.25 (107.95)
Compression Ratio	9.94:1
Intake Air Method	Naturally Aspirated
Number of Main Bearings	5
Connecting Rods	Forged Steel, Fractured Split, Bushingless
Cylinder Head	Cast Iron
Cylinder Liners	Cast Iron
Ignition	Coil Near Plug Solid State Inductive
Piston Type	Cast Aluminum Flat Top
Crankshaft Type	Forged Steel
Lifter Type	Hydraulic Roller
Intake Valve Material	Stainless Steel
Exhaust Valve Material	Stainless Steel
Hardened Valve Seats	High Steel Iron Alloy

Engine Governing

Governor	Electronic
Frequency Regulation (Steady State)	0.25

Lubrication System

Oil Pump	Gear Driven
Oil Filter Type	Full Flow Spin-On Cartridge
Engine Oil Capacity: qt (L)	21 (20)

Cooling System

Cooling System Type	Pressurized Closed	
Fan Type	Pusher	
Fan Speed (rpm)	2,100	
Fan Diameter - in (mm)	20 (508)	_

Fuel System

Fuel Type	Natural Gas, Propane
Fuel Injection	Electronic
Fuel Shutoff	Dual
Operating Fuel Pressure (NG) - in	5 - 14 (1.2 - 3.5)
H_2O (kPa)	
Operating Fuel Pressure (LP) - in H ₂ O	7 - 14 (1.7 - 3.5)
(kPa)	

Engine Electrical System

System Voltage	12 VDC	
Battery Charger Alternator	Standard	_
Battery Size	See Battery Index 0161970SBY	_
Battery Voltage	12 VDC	_
Ground Polarity	Negative (-)	_

ALTERNATOR SPECIFICATIONS

Standard Model	K0080124Y21
Poles	4
Field Type	Revolving
Insulation Class — Rotor	Н
Insulation Class — Stator	Н
Total Harmonic Distortion (THD)	<5%
Telephone Interference Factor (TIF)	<50

Standard Excitation	Synchronous Brushless
Bearings	Sealed Ball
Coupling	Direct via Flexible Disc
Prototype Short Circuit Test	Yes
Voltage Regulator Type	Full Digital
Number of Sensed Phases	All
Regulation Accuracy (Steady State)	+0.25%

INDUSTRIAL SPARK-IGNITED GENERATOR SET

EPA Certified Stationary Emergency

GENERAC INDUSTRIAL POWER

OPERATING DATA

POWER RATINGS NATURAL GAS/PROPANE VAPOR

Natural Gas Propane Standby/Demand Prime Standby/Demand Prime Response Response Alternator Power Power Voltage Power Amps Amps Power Amps Amps Single-Phase 120/240 VAC 48 kW/48 50 kW/50 45 kW/45 A0050044N21 200 45 kW/45 kVA 188 208 188 @1.0pf kVÁ kVÁ kVÁ Single-Phase 120/240 VAC 50 kW/50 50 kW/50 45 kW/45 A0060044N21 208 45 kW/45 kVA 188 208 188 @1.0pf kVA kVA kVA 50 kW/63 Three-Phase 120/208 VAC 48 kW/48 45 kW/56 K0050124Y21 45 kW/56 kVA 167 156 174 156 @0.8pf kVÁ kVÁ kVÁ Three-Phase 120/208 VAC 50 kW/63 50 kW/50 45 kW/56 K0060124Y21 174 45 kW/56 kVA 174 156 156 @0.8pf kVA kVA kVA Three-Phase 120/240 VAC 48 kW/48 50 kW/63 45 kW/56 45 kW/56 kVA 135 K0050124Y21 144 150 135 @0.8pf kVÁ kVÁ kVA Three-Phase 120/240 VAC 50 kW/50 50 kW/63 45 kW/56 K0060124Y21 150 45 kW/56 kVA 135 150 135 @0.8pf kVÁ kVÁ kVA Three-Phase 277/480 VAC 50 kW/50 50 kW/63 45 kW/56 K0050124Y21 75 45 kW/56 kVA 68 75 68 @0.8pf kVÁ kVÁ kVÁ Three-Phase 277/480 VAC 50 kW/50 50 kW/63 45 kW/56 45 kW/56 kVA K0060124Y21 75 68 75 68 @0.8pf kVA kVA kVA Three-Phase 346/600 VAC 50 kW/50 50 kW/63 45 kW/56 L008006N21 60 45 kW/56 kVA 54 60 54 @0.8pf kVÁ kVÁ kVA Three-Phase 346/600 VAC 50 kW/50 50 kW/63 45 kW/56 L010006N21 60 45 kW/56 kVA 54 54 60 @0.8pf kVA kVA kVA

STARTING CAPABILITIES (SKVA)

sKVA vs. Voltage Dip				
277/480 VAC	30%	208/240 VAC	30%	
K0080124Y21	98	K0080124Y21	75	
K0080124Y21	124	K0100124Y21	95	

INDUSTRIAL SPARK-IGNITED GENERATOR SET

EPA Certified Stationary Emergency



OPERATING DATA

FUEL CONSUMPTION RATES*

Natura	al Gas – scfh (m3,	/hr)	Pro	pane – scfh (m3/h	nr)
Percent Load	Standby	Prime	Percent Load	Standby	Prime
25%	204 (5.8)	201 (5.7)	25%	107 (3.0)	105 (3.0)
50%	343 (9.7)	298 (8.4)	50%	155 (4.4)	138 (3.9)
75%	456 (12.9)	394 (11.2)	75%	198 (5.6)	172 (4.9)
100%	621 (17.6)	495 (14.0)	100%	249 (7.1)	209 (5.9)
*Fuel supply installation must accommodate fuel consumption rates at 100% load.					

COOLING

		Standby	Prime
Air Flow (Fan Air Flow Across Radiator) - Open Set	cfm (m3/min)	3,511 (99	.4)
Coolant Flow	gpm (Lpm)	38 (142.)	7)
Coolant System Capacity	gal (L)	3 (11.4)	
Maximum Operating Ambient Temperature	°F (°C)	122 (50	
Maximum Operating Ambient Temperature (Before Derate)		See Bulletin No. 01	99270SSD
Maximum Radiator Backpressure	in H20 (kPa)	0.5 (0.12	2)

COMBUSTION AIR REQUIREMENTS

	Standby	Prime
Flow at Rated Power cfm (m ³ /min)	99.7 (2.8)	90.3 (2.6)

ENGINE

		Standby	Prime
Rated Engine Speed: RPM	rpm	1,800	1,800
Horsepower at Rated kW**	hp	77	69
Piston Speed	ft/min (m/ min)	1,275 (389)	1,275 (389)
BMEP	psi (kPa)	126 (865)	113 (779)
** Refer to "Emissions Data Sheet" for maximum bHP for EPA and			

 $[\]ensuremath{^{**}}$ Refer to "Emissions Data Sheet" for maximum bHP for EPA and SCAQMD permitting purposes.

EXHAUST

		Standby	Prime
Exhaust Flow (Rated Output)	cfm (m3/ min)	279 (7.9)	256 (7.2)
Maximum Exhaust Back pressure	in Hg (Kpa)	0.75 (2.54)	0.75 (2.54)
Exhaust Temp (Rated Output - Post Silencer)	°F (°C)	1,361 (738.3)	1,361 (738.3)

Deration - Operational characteristics consider maximum ambient conditions. Derate factors may apply under atypical site conditions.

Please contact a Generac Power Systems Industrial Dealer for additional details. All performance ratings in accordance with ISO3046, BS5514, ISO8528, and DIN6271 standards.


Standby - See Bulletin 0187500SSB Prime - See Bulletin 0187510SSB


INDUSTRIAL SPARK-IGNITED GENERATOR SET

EPA Certified Stationary Emergency




DIMENSIONS AND WEIGHTS*






OPEN SET (Includes Exhaust Flex)


L x W x H - in (mm)	78.1 (1,984) x 37.3 (947) x 44.4 (1,128)
Weight lbs (kg)	1,675 - 1,748 (760 - 793)






WEATHER PROTECTED ENCLOSURE


WEATHER THOTEOTED ENGLOSOME		
L x W x H - in (mm)	94.8 (2,408) x 38.0 (965) x 57.5 (1,461)	
Weight lbs (kg)	Steel: 2,160 - 2,233 (980 - 1,013) Aluminum: 1,894 - 1,965 (859 - 891)	






LEVEL 1 ACOUSTIC ENCLOSURE

ELVEL I ACCOUNT ENCECOCIE			
L x W x H - in (mm)	94.8 (2,408) x 38.0 (965) x 57.5 (1,461)		
Weight lbs (kg)	Steel: 2,258 - 2,329 (1,024 - 1,056) Aluminum: 1,987 - 2,061 (901 - 935)		





LEVEL 2 ACOUSTIC ENCLOSURE

L x W x H - in (mm)	94.8 (2,408) x 38.0 (965) x 57.5 (1,461)
Weight lbs (kg)	Steel: 2,341 - 2,414 (1,062 - 1,095) Aluminum: 2,071 - 2,144 (939 - 972)

* All measurements are approximate and for estimation purposes only.

YOUR FACTORY RECOGNIZED GENERAC INDUSTRIAL DEALER

Specification characteristics may change without notice. Dimensions and weights are for preliminary purposes only. Please consult a Generac Power Systems Industrial Dealer for detailed installation drawings